

APR 003
Fusion DMX Splitter
1.5.1

01 July 1999



The Fusion[®] DMX Splitter 1.5.1 sorts out expensive DMX problems.....

.....inexpensively



A Product Solution

Celco's Fusion DMX Splitter 1.5.1 solves many problems associated with DMX512.

Just look at these features:

✓ **1 Input, 5 Outputs and Link-On**
input on 5 pin XLR male connector.

Link on 5 pin XLR female connector.

Outputs 1 to 4 on 5 pin XLR female connectors.

Output 5 (pair) on 3 pin XLR female connectors,
one with reverse polarity.

All **Neutric** connectors

- ✓ **Signal Regeneration**
The DMX512 input signal is regenerated (buffered) and transmitted on outputs 1 through 5.
- ✓ **Output Protection**
Outputs 1 to 4 are optically isolated from the input.
- ✓ **Built in Power Supply**
The buffer unit has its own built in power supply with a captive cable so there are no connectors to fall out.
- ✓ **Status LED**
The two status LEDs indicate Power ON (Red) and DMX Receive (Green).
- ✓ **Other features**
1 x M10 threaded insert for mounting or hook clamp attachment

Rugged, black powder coated, die-cast case. Unit dimensions, 125mm x 125mm x 80mm, weight 1.1kg

CE approved, conforming to EN50081-1 and EN50082-1
- ✓ **Availability**
The Fusion DMX Splitter 1.5.1 is available from stock. Contact your Celco Dealer or Celco direct on tel +44 (0) 20 8699 6788, fax +44 (0) 20 8699 5056 or email sales@celco.co.uk